




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁷ : H04B 1/707		A1	(11) International Publication Number: WO 00/25439
		(43) International Publication Date: 4 May 2000 (04.05.00)	
(21) International Application Number: PCT/US99/25144 (22) International Filing Date: 26 October 1999 (26.10.99) (30) Priority Data: 09/182,367 27 October 1998 (27.10.98) US (71) Applicant: QUALCOMM INCORPORATED [US/US]; 5775 Morehouse Drive, San Diego, CA 92121-1714 (US). (72) Inventors: LUNDBY, Stein; 1037 Diamond Street, San Diego, CA 92109 (US). RAZOUMOV, Leonid; Apartment 3N, 3700 19th Avenue, San Diego, CA 92103 (US). WHEATLEY, Charles, E., III; 2208 Caminito Del Barco, Del Mar, CA 92014 (US). (74) Agents: MILLER, Russell, B. et al.; Qualcomm Incorporated, 5775 Morehouse Drive, San Diego, CA 92121-1714 (US).		(81) Designated States: AE, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CR, CU, CZ, DE, DK, DM, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, UZ, VN, YU, ZA, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG). Published <i>With international search report.</i> <i>Before the expiration of the time limit for amending the</i> <i>claims and to be republished in the event of the receipt of</i> <i>amendments.</i>	

(54) Title: METHOD AND APPARATUS FOR MULTIPATH DEMODULATION IN A CODE DIVISION MULTIPLE ACCESS COMMUNICATION SYSTEM

HAND OF 4 FINGERS AT 1/2 CHIP SEPARATION



(57) Abstract

Multipath RAKE receiver structure that allows for the concurrent demodulation of multipath signals that arrive at the receiver at arbitrarily low arrival time differences. The fingers (200) are set to be a fixed offset from one another. One finger (200) tracks the shift in the peak of the multipath component and the additional fixed offset fingers follow the tracking.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon	KR	Republic of Korea	PL	Poland		
CN	China	KZ	Kazakhstan	PT	Portugal		
CU	Cuba	LC	Saint Lucia	RO	Romania		
CZ	Czech Republic	LI	Liechtenstein	RU	Russian Federation		
DE	Germany	LK	Sri Lanka	SD	Sudan		
DK	Denmark	LR	Liberia	SE	Sweden		
EE	Estonia			SG	Singapore		

METHOD AND APPARATUS FOR MULTIPATH DEMODULATION IN A CODE DIVISION MULTIPLE ACCESS COMMUNICATION SYSTEM

5 BACKGROUND OF THE INVENTION

I. Field of the Invention

The present invention relates to communications. More particularly,
10 the present invention relates to a novel and improved method and apparatus for demodulating code division multiple access (CDMA) signals.

II. Description of the Related Art

15 In a wireless radiotelephone communication system, many users communicate over a wireless channel to connect to wireline telephone systems. Communication over the wireless channel can be one of a variety of multiple access techniques that allow a large number of users in a limited frequency spectrum. These multiple access techniques include time division
20 multiple access (TDMA), frequency division multiple access (FDMA), and code division multiple access (CDMA).

The CDMA technique has many advantages. An exemplary CDMA system is described in U.S. Patent No. 4,901,307, entitled "SPREAD SPECTRUM MULTIPLE ACCESS COMMUNICATION SYSTEM USING
25 SATELLITE OR TERRESTRIAL REPEATERS", assigned to the assignee of the present invention and incorporated by reference herein.

In the '307 patent, a multiple access technique is disclosed where a large number of mobile telephone system users, each having a transceiver, communicate through satellite repeaters or terrestrial base stations using
30 CDMA spread spectrum communication signals. The base station-to-mobile station signal transmission path is referred to as the forward link and the mobile station-to-base station signal transmission path is referred to as the reverse link.

In using CDMA communications, the frequency spectrum can be
35 reused multiple times thus permitting an increase in system user capacity. Each base station provides coverage to a limited geographic area and links the

mobile stations in its coverage area through a cellular system switch to the public switched telephone network (PSTN). When a mobile station moves to the coverage area of a new base station, the routing of that user's call is transferred to the new base station.

5 The CDMA modulation techniques discussed in the '307 patent and in U.S. Patent No. 5,102,459 entitled "SYSTEM AND METHOD FOR GENERATING SIGNAL WAVEFORMS IN A CDMA CELLULAR TELEPHONE SYSTEM", assigned to the assignee of the present invention and incorporated by reference herein, mitigate the special problems of the
10 terrestrial channel, such as multipath and fading. Instead of being an impediment to system performance, as it is with narrowband systems, separable multipaths can be diversity combined in a mobile rake receiver for enhanced modem performance. The use of a RAKE receiver for improved reception of CDMA signals is disclosed in U.S. Patent No. 5,109,390, entitled
15 "DIVERSITY RECEIVER IN A CDMA CELLULAR TELEPHONE SYSTEM", assigned to the assignee of the present invention and incorporated by reference herein. In the mobile radio channel, multipath is created by reflection of the signal from obstacles in the environment, such as buildings, trees, cars, and people. In general the mobile radio channel is a time varying
20 multipath channel due to the relative motion of the structures that create the multipath. For example, if an ideal impulse is transmitted over the time varying multipath channel, the received stream of pulses would change in time location, attenuation, and phase as a function of the time that the ideal impulse was transmitted.

25 The multipath properties of the terrestrial channel produce, at the receiver, signals having traveled several distinct propagation paths. One characteristic of a multipath channel is the time spread introduced in a signal that is transmitted through the channel. As described in the '340 patent, the spread spectrum pseudonoise (PN) modulation used in a CDMA system
30 allows different propagation paths of the same signal to be distinguished and combined, provided the difference in path delays exceeds the PN chip duration. If a PN chip rate of approximately 1 MHz is used in a CDMA system, the full spread spectrum processing gain, equal to the ratio of the spread

bandwidth to the system data rate, can be employed against paths having delays that differ by more than one microsecond. A one microsecond path delay differential corresponds to a differential path distance of approximately 300 meters. Another characteristic of the multipath channel is that each path
5 through the channel may cause a different attenuation factor. For example, if an ideal impulse is transmitted over a multipath channel, each pulse of the received stream of pulses generally has a different signal strength than other received pulses.

Yet another characteristic of the multipath channel is that each path
10 through the channel may cause a different phase on the signal. If, for example, an ideal impulse is transmitted over a multipath channel, each pulse of the received stream of pulses generally has a different phase than other received pulses. This can result in signal fading.

A fade occurs when multipath vectors are added destructively, yielding
15 a received signal that is smaller than either individual vector. For example, if a sine wave is transmitted through a multipath channel having two paths where the first path has an attenuation factor of X dB, a time delay of d with a phase shift of Q radians, and the second path has an attenuation factor of X dB, a time delay of d with a phase shift of $Q + \pi$ radians, no signal would be
20 received at the output of the channel.

As described above, in current CDMA demodulator structures, the PN chip interval defines the minimum separation two paths must have in order to be combined. Before the distinct paths can be demodulated, the relative arrival times (or offsets) of the paths in the received signal must first be
25 determined. The demodulator performs this function by "searching" through a sequence of offsets and measuring the energy received at each offset. If the energy associated with a potential offset exceeds a certain threshold, a demodulation element, or "finger" may be assigned to that offset. The signal present at that path offset can then be summed with the
30 contributions of other fingers at their respective offsets.

A method and apparatus of finger assignment based on searcher and finger energy levels is disclosed in U.S. Patent No. 5,490,165, entitled "FINGER ASSIGNMENT IN A SYSTEM CAPABLE OF RECEIVING

MULTIPLE SIGNALS", assigned to the assignee of the present invention and incorporated by reference herein. In the exemplary embodiment, the CDMA signals are transmitted in accordance with the Telecommunications Industry Association TIA/EIA/IS-95-A, entitled "MOBILE STATION-BASE STATION
5 COMPATIBILITY STANDARD FOR DUAL-MODE WIDEBAND SPREAD SPECTRUM CELLULAR SYSTEM". An exemplary embodiment of the circuitry capable of demodulating IS-95 forward link signals is described in detail in U.S. Patent No. 5,764,592, entitled "MOBILE DEMODULATOR ARCHITECTURE FOR A SPREAD SPECTRUM MULTIPLE ACCESS
10 SYSTEM", assigned to the assignee of the present invention and incorporated by reference herein. An exemplary embodiment of the circuitry capable of demodulating IS-95 reverse link signals is described in detail in U.S. Patent No. 5,654,979, entitled "CELL SITE DEMODULATOR ARCHITECTURE FOR A SPREAD SPECTRUM MULTIPLE ACCESS COMMUNICATION SYSTEM,"
15 assigned to the assignee of the present invention and incorporated by reference herein.

FIG. 1 shows an exemplary set of signals from a base station arriving at the mobile station. It will be understood by one skilled in the art that FIG. 1 is equally applicable to the signals from a mobile station arriving at the base
20 station. The vertical axis represents the power received on a decibel (dB) scale. The horizontal axis represents the delay in the arrival time of a signal due to multipath delays. The axis (not shown) going into the page represents a segment of time. The signals in the common plane traveled along different paths arriving at the receiver at the same time, but having been transmitted
25 at different times.

In a common plane, peaks to the right were transmitted at an earlier time by the base station than peaks to the left. For example, the left-most peak spike 2 corresponds to the most recently transmitted signal. Each signal spike 2 - 7 has traveled a different path and therefore exhibits a different time
30 delay and a different amplitude response.

The six different signal spikes represented by spikes 2-7 are representative of a severe multipath environment. Typical urban

environments produce fewer usable paths. The noise floor of the system is represented by the peaks and dips having lower energy levels.

The task of the searcher is to identify the delay as measured by the horizontal axis of signal spikes 2 - 7 for potential finger assignment. The task
5 of the finger is to demodulate one of a set of the multipath peaks for combination into a single output. It is also the task of a finger, once assigned to a multipath peak, to track that peak as it may move in time.

The horizontal axis can also be thought of as having units of PN offset. At any given time, the mobile station receives a variety of signals from a base
10 station, each of which has traveled a different path and may have a different delay than the others. The base station's signal is modulated by a PN sequence. A local copy of the PN sequence is also generated at the mobile station. Also at the mobile station, each multipath signal is individually demodulated with a PN sequence code aligned to its received time offset. The
15 horizontal axis coordinates can be thought of as corresponding to the PN sequence code offset that would be used to demodulate a signal at that coordinate.

Note that each of the multipath peaks varies in amplitude as a function of time, as shown by the uneven ridge of each multipath peak. In the limited
20 time shown, there are no major changes in the multipath peaks. Over a more extended time range, multipath peaks disappear and new paths are created as time progresses. The peaks can also slide to earlier or later offsets as the path distances change when the mobile station moves relative to the base station. Each finger tracks these small variations in the signal assigned to it.

25 In narrowband systems, the existence of multipath in the radio channel can result in severe fading across the narrow frequency band being used. Such systems are capacity constrained by the extra transmit power needed to overcome a deep fade. As noted above, CDMA signal paths may be discriminated and diversity combined in the demodulation process.

30 Three major types of diversity exist: time diversity, frequency diversity, and space/path diversity. Time diversity can best be obtained by the use of repetition, time interleaving, and error correction and detection coding that

introduce redundancy. A system may employ each of these techniques as a form of time diversity.

CDMA, by its inherent wideband nature, offers a form of frequency diversity by spreading the signal energy over a wide bandwidth. The
5 frequency selective fading that can cause a deep fade across a narrowband system's frequency bandwidth usually only affects a fraction of the frequency band employed by the CDMA spread spectrum signal.

The rake receiver provides path diversity through its ability to combine multipath delayed signals; all paths that have a finger assigned to them must
10 fade together before the combined signal is degraded. Additional path diversity is obtained through a process known as "soft hand-off" in which multiple simultaneous, redundant links from two or more base stations can be established with the mobile station. This supports a robust link in the challenging environment at the cell boundary region. Examples of path
15 diversity are illustrated in U.S. Patent No. 5,101,501 entitled "SOFT HAND-OFF IN A CDMA CELLULAR TELEPHONE SYSTEM", and U.S. Patent No. 5,109,390 entitled "DIVERSITY RECEIVER IN A CDMA CELLULAR TELEPHONE SYSTEM", both assigned to the assignee of the present invention and incorporated by reference herein.

20 Both the cross-correlation between different PN sequences and the autocorrelation of a PN sequence, for all time shifts other than zero, have a nearly zero average value. This allows the different signals to be discriminated upon reception. Autocorrelation and cross-correlation require that logical "0" take on a value of "1" and logical "1" take on a value of "-1",
25 or a similar mapping, in order that a zero average value be obtained.

However, such PN signals are not orthogonal. Although the cross-correlation essentially averages to zero over the entire sequence length for a short time interval, such as an information bit time, the cross-correlation is a random variable with a binomial distribution. As such, the signals interfere
30 with each other in much the same manner as if they were wide bandwidth Gaussian noise at the same power spectral density.

It is well known in the art that a set of n orthogonal binary sequences, each of length n , for n any power of 2 can be constructed (see *Digital*

Communications with Space Applications, S.W. Golomb et al., Prentice-Hall, Inc., 1964, pp. 45-64). In fact, orthogonal binary sequence sets are also known for most lengths that are multiples of four and less than two hundred. One class of such sequences that is easy to generate is called the Walsh function; a

5 Walsh function of order n can be defined recursively as follows:

$$W(n) = \begin{vmatrix} W(n/2) & W(n/2) \\ W(n/2) & W'(n/2) \end{vmatrix} \quad (1)$$

where W' denotes the logical complement of W , and $W(1) = |0|$.

10 A Walsh sequence or code is one of the rows of a Walsh function matrix. A Walsh function matrix of order n contains n sequences, each of length n Walsh chips. A Walsh function matrix of order n (as well as other orthogonal functions of length n) has the property that over the interval of n bits, the cross-correlation between all the different sequences within the set is

15 zero. Every sequence in the set differs from every other sequence in exactly half of its bits. It should also be noted that there is always one sequence containing all zeroes and that all the other sequences contain half ones and half zeroes.

In the system described in the '459 patent, the call signal begins as a 9600

20 bit per second information source which is then converted by a rate 1/2 forward error correction encoder to a 19,200 symbols per second output stream. Each call signal broadcast from a cell is covered with one of sixty-four orthogonal Walsh sequences, each sixty-four Walsh chips, or one symbol, in duration. Regardless of the symbol being covered, the orthogonality of all

25 Walsh sequences ensures that all interference from other user signals in that cell are canceled out during symbol integration. The non-orthogonal interference from other cells limits capacity on the forward link.

Each base station in a CDMA system transmits in the same frequency band using the same PN sequence, but with a unique offset relative to an

30 unshifted PN sequence aligned to a universal time reference. The PN spreading rate is the same as the Walsh cover rate, 1.2288 MHz, or 64 PN chips per symbol. In the preferred embodiment, each base station transmits a pilot

reference. In the description of the present invention different information is transmitted on the I and Q channels which increases the capacity of the system.

The pilot channel is a "beacon" transmitting a constant zero symbol
5 and spread with the same I and Q PN sequences used by the traffic bearing signals. In the exemplary embodiment, the pilot channel is covered with the all zero Walsh sequence 0. During initial system acquisition the mobile searches all possible shifts of the PN sequence and once it has found a base station's pilot, it can then synchronize itself to system time. As detailed
10 below, the pilot plays a fundamental role in the mobile demodulator rake receiver architecture well beyond its use in initial synchronization.

FIG. 2 depicts a generic rake receiver demodulator 10 for receiving and demodulating the forward link signal 20 arriving at the antenna 18. The analog transmitter and receiver 16 contain a QPSK downconverter chain that
15 outputs digitized I and Q channel samples 32 at baseband. The sampling clock, CHIPX8 40, used to digitize the receive waveform, is derived from a voltage controlled temperature compensated local oscillator (TCXO).

The demodulator 10 is supervised by a microprocessor 30 through the databus 34. Within the demodulator, the I and Q samples 32 are provided to a
20 plurality of fingers 12a-c and a searcher 14. The searcher 14 searches out windows of offsets likely to contain multipath signal peaks suitable for assignment of fingers 12a-c. For each offset in the search window, the searcher 14 reports the pilot energy it found at that offset to the microprocessor. The fingers 12a-c are then surveyed, and those unassigned or
25 tracking weaker paths are assigned by the microprocessor 30 to offsets containing stronger paths identified by searcher 14.

Once a finger 12a-c has locked onto the multipath signal at its assigned offset it then tracks that path on its own until the path fades away or until it is reassigned using its internal time tracking loop. This finger time tracking
30 loop measures energy on either side of the peak at the offset at which the finger is currently demodulating. The difference between these energies forms a metric which is then filtered and integrated.

The output of the integrator controls a decimator that selects one of the input samples over a chip interval to use in demodulation. If a peak moves, the finger adjusts its decimator position to move with it. The decimated sample stream is then despread with the PN sequence consistent with the offset to which the finger is assigned. The despread I and Q samples are summed over a symbol to produce a pilot vector (P_I , P_Q). These same despread I and Q samples are Walsh uncovered using the Walsh code assignment unique to the mobile user and the uncovered, despread I and Q samples are summed over a symbol to produce a symbol data vector (D_I , D_Q).
10 The dot product operator is defined as

$$\mathbf{P}(n) \bullet \mathbf{D}(n) = P_I(n)D_I(n) + P_Q(n)D_Q(n), \quad (2)$$

where $P_I(n)$ and $P_Q(n)$ are respectively the I and Q components of the pilot vector \mathbf{P} for symbol n and $D_I(n)$ and $D_Q(n)$ are respectively the I and Q components of the data vector \mathbf{D} for symbol n .
15

Since the pilot signal vector is much stronger than the data signal vector it can be used as an accurate phase reference for coherent demodulation; the dot product computes the magnitude of the data vector component in phase with the pilot vector. As described in U.S. Patent No. 5,506,865, entitled "PILOT CARRIER DOT PRODUCT CIRCUIT" and assigned to the assignee of the present invention and incorporated by reference herein, the dot product weights the finger contributions for efficient combining, in effect scaling each finger symbol output 42a-c by the relative strength of the pilot being received by that finger. Thus the dot product performs the dual role of both phase projection and finger symbol weighting needed in a coherent rake receiver demodulator.
20
25

Each finger has a lock detector circuit that masks the symbol output to the combiner 42 if its long term average energy does not exceed a minimum threshold. This ensures that only fingers tracking a reliable path will contribute to the combined output, thus enhancing demodulator performance.
30

Due to the relative difference in arrival times of the paths to which each finger 12a-c is assigned, each finger 12a-c has a deskew buffer that aligns the finger symbol streams 42a-c so that the symbol combiner 22 can sum them together to produce a "soft decision" demodulated symbol. This symbol is weighted by the confidence that it correctly identifies the originally transmitted symbol. The symbols are sent to a deinterleaver/decoder circuit 28 that first frame deinterleaves and then forward error correction decodes the symbol stream using the maximum likelihood Viterbi algorithm. The decoded data is then made available to the microprocessor 30 or to other components, such as a speech vocoder, for further processing.

To demodulate correctly, a mechanism is needed to align the local oscillator frequency with the clock used at the cell to modulate the data. Each finger makes an estimate of the frequency error by measuring the rotation rate of the pilot vector in QPSK I, Q space using the cross product vector operator:

$$P(n) \times P(n-1) = P_I(n)P_Q(n-1) - P_I(n-1)P_Q(n) \quad (3)$$

The frequency error estimates from each finger 44a-c are combined and integrated in frequency error combiner 26. The integrator output, LO_ADJ 36, is then fed to the voltage control of the TCXO in the analog transmitter and receiver 16 to adjust the clock frequency of the CHIPX8 clock 40, thus providing a closed loop mechanism for compensating for the frequency error of the local oscillator.

As described above, in current demodulator structures, a path must differ by at least one PN chip to have a separate finger allocated to its demodulation. However, there are cases when paths differ by less than a PN chip interval in the time, this situation leads to the existence of a "fat path". Under traditional demodulator implementations, only one finger could be allocated to demodulate the fat path. One of the reasons for this is that once assigned to a path, the finger tracks the path movement independently. Without central coordination of the fingers multiple fingers will converge

to the same peak of the fat path. In addition, the searcher tends to get confused when paths are tracked which are too close to one another

On an orthogonal forward link, there is a great deal of energy in each of the paths because all of the energy from the base station to all mobiles is transmitted using the same PN offset which are channelized by use of orthogonal code sequences. Moreover, orthogonal code sequences have poor autocorrelation in that the correlation between orthogonal code sequences is high. Thus, when paths on the forward link differ by less than a PN chip interval, the signals cannot be distinguished from one another by the outer PN spreading nor is the coding gain of the orthogonal spreading realized because of the time shift. The energy of the close multipath components in this case serves as noise and substantially degrades the performance of the demodulator assigned to the fat path. On the reverse link, close multipath components can also cause degradation of the demodulator assigned to the fat path.

The present invention is described with respect to the improvement of the demodulation of the forward link. However, the present invention is equally applicable to improving the demodulation of the reverse link.

SUMMARY OF THE INVENTION

The present invention is a novel and improved method and apparatus for multipath demodulation in a code division multiple access communication system. In current demodulator architectures, an accumulator is provided for each finger and the combining operation is performed subsequent to the accumulation operation. In the present invention, a demodulator structure is described that reduces the amount of hardware and software in the receiver by reducing the number of symbol accumulators to one.

Moreover, the present invention describes a demodulator structure that allows for the concurrent demodulation of multipath signals that arrive at the receiver at arbitrarily low arrival time differences. As described above, traditional demodulator structures prohibit the assignment of arbitrarily close fingers because the fingers converge to the peak of the path,

negating any possible benefit sought from assigning the fingers to paths that are very close. In the present invention, the fingers are set to be a fixed offset from one another. In the present invention, one finger tracks the shift in the peak of the multipath component and the additional fixed offset
5 fingers follow the tracking.

BRIEF DESCRIPTION OF THE DRAWINGS

The features, objects, and advantages of the present invention will
10 become more apparent from the detailed description set forth below when taken in conjunction with the drawings in which like reference characters identify correspondingly throughout and wherein:

FIG. 1 represents an exemplary severe multipath signal condition;

FIG. 2 is a block diagram of a current demodulation system;

15 FIG. 3 is an illustration of a fat path situation in which a number of multipath components are very closely spaced with respect to one another in arrival times at the receiver;

FIG. 4 is an illustration of the receiver structure that provides for effective demodulation of the closely spaced multipath components;

20 FIG. 5 is an illustration of an improved demodulation structure that allows for a single accumulator in the receiver architecture;

FIG. 6 is a first embodiment of the fat path demodulator of the present invention wherein four fingers are used to demodulate four multipath components with arrival times offset from one another by half of one PN
25 chip wherein the method of path discrimination is through the offsetting of the PN sequences with accompanying deskewing prior to combination;

FIG. 7 is a second embodiment of the fat path demodulator of the present invention wherein four fingers are used to demodulate four multipath components with arrival times offset from one another by half of
30 one PN chip wherein the received signal is delayed by varying amounts of times before being provided to the respective fingers;

FIG. 8 is a third embodiment of the fat path demodulator of the present invention wherein six fingers are used to demodulate six multipath components with arrival times offset from one another by half of one PN

chip wherein the received signal is delayed by varying amounts of times before being provided to the respective fingers;

FIG. 9 is a fourth embodiment of the fat path demodulator of the present invention wherein five fingers are used to demodulate five
5 multipath components with arrival times offset from one another by one third of one PN chip wherein the received signal is delayed by varying amounts of times before being provided to the respective fingers;

FIG. 10 illustrates an alternative embodiment that allows for elimination of the input switch;

10 FIG. 11 illustrates an alternative embodiment that allows for elimination of all but one Walsh sequence multiplier;

FIG. 12 illustrates an alternative embodiment that allows for the elimination of two demodulator structures; and

FIG. 13 illustrates an alternative embodiment that allows for the
15 elimination of two demodulators and allows the receiver to operate at the PN chip rate

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

20 FIG. 3 shows an exemplary set of signals from a base station arriving at the mobile station at a given time. It will be understood by one skilled in the art that FIG. 3 is equally applicable to the signals from a mobile station arriving at the base station. The vertical axis represents the power received
25 on a decibel (dB) scale. The horizontal axis represents the delay in the arrival time of a signal due to multipath delays. The signals on the x-axis traveled along different paths arriving at the receiver at the same time, but having been transmitted at different times.

In a common plane, peaks to the right were transmitted at an earlier
30 time by the base station than peaks to the left. For example, the left-most peak spike 50 corresponds to the most recently transmitted signal. Each signal spike 50, 54 and 58 has traveled a different path and therefore exhibits a different time delay and a different amplitude response.

The three different signal spikes represented by spikes 50, 54 and 58 are representative of a severe multipath environment. As described previously, the task of the searcher is to identify the delay as measured by the horizontal axis of signal spikes 50, 54 and 58 for potential finger assignment. However, in the present invention, the additional task of the searcher is to identify peak 54 as a fat path or set of multipath components to which the demodulator structure of the present invention is capable of effective demodulation of close multipath components. The task of each of the finger is to demodulate one of a set of the multipath peaks for combination into a single output. It is also the task of a finger, once assigned to a multipath peak, to track that peak as it may move in time.

FIG. 4 depicts the rake receiver demodulator 110 of the present invention for receiving and demodulating the forward link signal 120 arriving at the antenna 118 of the present invention. The analog transmitter and receiver 116 contain a QPSK downconverter chain that outputs digitized I and Q channel samples 132 at baseband. In an exemplary embodiment, the sampling clock, CHIPX8 140, used to digitize the receive waveform, is derived from a voltage controlled temperature compensated local oscillator (TCXO).

The demodulator 110 is supervised by a microprocessor 130 through the databus 134. Within the demodulator, the I and Q samples 132 are provided to a plurality of fingers 112a-c and a searcher 114. Although the exemplary embodiment is described in terms of QPSK demodulation, the present invention is equally applicable to BPSK, QAM (Quadrature Amplitude Modulation), M-ary PSK or any known modulation method. The searcher 114 searches out windows of offsets likely to contain multipath signal peaks suitable for assignment of fingers 112a-c. For each offset in the search window, the searcher 114 reports the pilot energy it found at that window of offsets to the microprocessor 130. In the present invention, microprocessor 130 determines where to assign fingers and determines whether and where to assign a fat path demodulators.

Searcher 114 reports the energies in a window around peaks 50, 54 and 58. Microprocessor 130 determine from the reported energies that peaks 50 and 58 were narrow and could be successfully demodulated with a single path

demodulator. Microprocessor 130 would also be able to identify the multipath component at peak 54 as a fat path and would assign for its demodulation the fat path demodulator of the present invention. So for example, fingers 112a and 112b demodulate single paths and are assigned to paths 50 and 58 of FIG. 3. Finger 112c, on the other hand, are directed by microprocessor 130 to perform a fat path demodulation and would be assigned to demodulate path 54.

FIG. 5 illustrates a novel RAKE receiver structure that uses a single accumulator instead of an accumulator for each finger as is provided in current RAKE receiver structures.. The digitized samples are provided to complex PN despreader 150 of demodulator 158. In the exemplary embodiment, the signals are complex PN spread as described in U.S. Patent Application Serial No. 08/856,428, entitled "REDUCED PEAK TO AVERAGE TRANSMIT POWER HIGH DATA RATE IN A CDMA WIRELESS COMMUNICATION SYSTEM," filed April 9, 1996, assigned to the assignee of the present invention and incorporated by reference herein, in accordance with the following equations:

$$I = I' PN_I + Q' PN_Q \quad (4)$$

$$Q = I' PN_Q - Q' PN_I \quad (5)$$

where PN_I and PN_Q are distinct PN spreading codes and I' and Q' are two channels being spread at the transmitter. Complex PN despreader 150 removes the complex spreading based on the PN codes, PN_I and PN_Q , to provide two complex PN despread signals.

The complex PN despread signals are provided to pilot filter 152 and complex conjugate multiplier 154. Pilot filter 152 uncovers the pilot signal in accordance with the orthogonal covering (W_{pilot}) and, in a preferred embodiment, provides some filtering to the resultant signal to remove the effects of noise on the received signal. In the exemplary embodiment, the pilot signal is covered using Walsh 0 which is the all zeroes Walsh sequence. Thus, uncovering the Walsh sequence is a no op and pilot filter 152 simply acts as a low pass filter to reduce the effect of channel noise.

Complex conjugate multiplier 154 multiplies the signal from complex PN despreader 150 by the conjugate of the filtered pilot signal from pilot filter 152. By multiplying the complex despread data by the conjugate of the signals from pilot filter 152, the demodulator removes any phase error from the received signal. In effect complex conjugate multiply circuit projects the received signal onto the pilot signal and outputs the magnitudes of the projections.

The signals from complex conjugate multiplier 154 are provided to Walsh multiplier 156. Walsh multiplier 156 multiplies the I and Q traffic channels with the orthogonal traffic channel covering sequences W_{traffic} . The traffic channel data is then output to symbol combiner 160. Demodulators 158b and 158c demodulate the received signals for different multipath components using different PN offsets of PN_I and PN_Q and are deskewed prior to being provided to combiner 160. In the exemplary embodiment, only signals with energies exceeding a predetermined threshold are combined in combiner 160. The combined symbol energies are thereafter provided to accumulator 162 which accumulates the combined energy values over Walsh sequence intervals to provide estimates of the I + Q values.

In an alternative embodiment, complex conjugate multiplier 154 and Walsh multiplier 156 can be interchanged without the need for altering any other functions. It will be understood by one skilled in the art that the simple rearrangements of elements are well known in the art and are within the scope of the present invention.

Before turning our attention to the implementation of the fat finger demodulator structure, let us briefly examine the process that allows combining of the received signals in a CDMA communication system. Referring back to FIG. 1, it was described earlier that the peaks on the common plane were transmitted at different times and followed different propagation paths so as to arrive at the receiver at a common time. As described above, the signal in peak 2 corresponds to the most recently transmitted signal. The signal in peak 3 was transmitted approximately 2 PN chip intervals in time later. In order to combine the information in peak 2 with the information in peak 3, the information from peak 2 must be delayed

by two PN chip intervals before being combined with the information from peak 3 so that different version of the same information are combined.

The proposed fat path demodulators take advantage of both PN shifting and time delay to provide for deskewing of the information. Turning to FIG. 6, a fat path demodulator is illustrated which performs demodulation of fat paths comprising a set of closely spaced multipath components with energy spread across a plurality of PN chips. In FIG. 6, four demodulators 200a-200d are provided to demodulate paths that are a fixed half PN chip distance from one another. The demodulators move together demodulating a PN offsets that are offset from one another by fixed increments. In an alternative embodiment, the microprocessor in the receiver could be used to determine the shape of the fat path and would adjust the values of delay elements in accordance with the shape of the path grouping. In the exemplary embodiment, one of the demodulators is the master and tracks the peak of set of multipath signals and the other demodulators act as slaves and follow the tracking of the master demodulator.

Demodulator 200a and demodulator 200c demodulate the received signal using PN sequences that are offset from one another by one PN chip interval. This can be seen by observing that the signal provided to input 198 is provided directly to demodulators 200a and 200c. Demodulator 200a demodulates the received signal in accordance with a PN offset from PN generator 206 that is delayed by one PN chip interval by delay element 208 and in accordance with a Walsh sequence from Walsh generator 218 that is delayed by one PN chip interval by delay element 216.

As described with respect to FIG. 1, the signal demodulated by demodulator 200a followed a propagation path that took one PN chip longer to traverse than the propagation path upon which the signal demodulated by demodulator 200c followed. In order to properly combine the information, delay element 220 delays the data demodulated by demodulator 200c prior to combining with the demodulated data from demodulator 200a.

The same combining operation is performed with respect to the signals demodulated by demodulators 200b and 200d. Demodulators 200b and 200d demodulate signal that have traversed paths that differ by one half PN chip

interval from the signals demodulated by demodulators 200a and 200c, respectively. The deskewing of the half chip path difference is not performed by a delays but rather is inherent in the performance of the signal combining operation in combiner element 224 which combines when the demodulated
5 data from demodulators 200b and 200d is available to combiner element 224. This intrinsically means that the information from demodulators 200a and 200c was provided a half PN cycle earlier than the demodulated information from demodulators 200b and 200d in essence performing the additional deskewing operation. One skilled in the art will recognize that this operation
10 could be performed by placing addition $\frac{1}{2}$ PN chip delays on the outputs of demodulators 200b and 200d.

Moving to the detailed operation of the demodulator of FIG. 6, baseband samples at twice the PN chip rate are provided to switch 202. Switch 202 switches between outputs 198 and 199 at twice the rate of the PN chip
15 cycle. The first base band sample is provided to demodulators 200a and 200c. The next baseband sample that arrives one half PN chip interval later is provided to demodulators 200b and 200d.

The first sample is provided through switch 202 on line 198 to demodulator 200a. The sample is PN descrambled in PN descrambling
20 element 204a. In the exemplary embodiment, PN descrambling element 204a descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 206. The PN sequences are delayed by delay element 208 by one PN chip period. The complex despreading operation is performed as described above with respect to complex despreading element
25 150 of FIG. 5.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 212a and to pilot filter 210a. Complex conjugate multiplier removes phase ambiguities that are introduced by the propagation path. Pilot filter 210a uncovers the pilot channel in accordance with the
30 Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 210a is simply a low pass filter which the noise from the pilot signal. The complex conjugate of the filtered pilot

signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 212a which computes the dot product of the pilot channel and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 214a.

5 Walsh sequence multiplier 214a multiplies the input scalar sequence from complex conjugate multiplier 212a by the traffic channel Walsh sequence from Walsh generator 218 which is delayed by one PN chip interval by delay element 216. The multiplied sequence is then provided to combiner element 224.

10 The first sample is redundantly provided through switch 202 on line 198 to demodulator 200c. The sample is PN descrambled in PN descrambling element 204c. In the exemplary embodiment, PN descrambling element 204c descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 206. The PN sequences are provided directly to PN
15 descrambling element 204c which results in the sample being demodulated by a PN sequence offset from the sequence used by demodulator 200a by one PN chip interval.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 212c and to pilot filter 210c. Pilot filter 210c
20 uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 210c is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal
25 and the complex PN despread sequences are multiplied in complex conjugate multiplier 212c which computes the dot product of the pilot channel and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 214c.

Walsh sequence multiplier 214c multiplies the input scalar sequence
30 from complex conjugate multiplier 212c by the traffic channel Walsh sequence from Walsh generator 218. The multiplied sequence is then provided to summing means 224.

After one half PN chip interval, switch 202 toggles so as to put the next sample, received one half PN chip interval later, on input line 199 to demodulators 200b and 200d. Within demodulator 200b, the sample is PN descrambled in PN descrambling element 204b. As described previously PN descrambling element 204b descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 206b. The PN sequences are delayed by delay element 208 by one PN chip period.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 212b and to pilot filter 210b. Pilot filter 210b uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 210b is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 212b which computes the dot product of the pilot channel and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 214b.

Walsh sequence multiplier 214b multiplies the input scalar sequence from complex conjugate multiplier 212b by the traffic channel Walsh sequence from Walsh generator 218 which is delayed by one PN chip interval by delay element 216. The multiplied sequence is then provided to combiner means 224.

The second sample is redundantly provided through switch 202 on line 199 to demodulator 200d. The second sample is PN descrambled in PN descrambling element 204d. In the exemplary embodiment, PN descrambling element 204d descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 206. The PN sequences are provided directly to PN descrambling element 204d which results in the sample being demodulated by a PN sequence offset from the sequence used by demodulator 200b by one PN chip interval.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 212d and to pilot filter 210d. Pilot filter 210d uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 210d is simply

a low pass filter that removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 212d which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to
5 provide a scalar sequence to Walsh sequence multiplier 214d.

Walsh sequence multiplier 214d multiplies the input scalar sequence from complex conjugate multiplier 212d by a Walsh sequence from Walsh generator 218. The multiplied sequence is then provided to combiner 224.

After the demodulated signals from demodulators 200b and 200d have
10 been provided to combiner element 224, combiner element 224 combines the energies and outputs the combined energy values to accumulator 226. Accumulator 226 performs the integration or summation of the input symbols over the Walsh symbol interval. Combiner element 224 can perform the combination in a variety of ways. Combiner element 224 could sum only
15 demodulated data with energy above a threshold value or could sum all of the energies. Alternatively, combiner 224 could select the demodulated data with the greatest energy. In an alternative embodiment, combiner 224 combines the energy based on the power of the demodulated pilot from pilot filter 210. For the sake of clarity, optional lines from pilot filters 210 to
20 combiner 224 have been omitted.

In FIG. 7, a second fat path demodulator is illustrated where the delays are applied to the input signal instead of the demodulation elements. In FIG. 7, four demodulators 300a-300d are provided to demodulate paths that are a fixed half PN chip distance from one another. The demodulators move
25 together demodulating PN offsets that are offset from one another by fixed increments. As described previously a microprocessor could be used to vary the amount of delay provided by delay elements 320 and 322. In the exemplary embodiment, one of the demodulators is the master and tracks the peak of set of multipath signals and the other demodulators act as slaves and
30 follow the master demodulator. In the exemplary embodiment, a metric such as the power from pilot filter 210 can be used by the master finger to track the movement of the peak.

Demodulator 300a and demodulator 300c demodulate the received signal that are delayed with respect to one another by one PN chip interval. The signal provided to input 298 is provided directly to demodulator 300a. The signal is delayed by one PN chip interval by delay element 320 prior to
5 being provided to demodulator 300c. If a first version of the transmitted signal traverses a first propagation path to be successfully demodulated by demodulator 300a, then a second version of the transmitted signal would need to traverse a second propagation path requiring a PN chip interval longer than the time required to traverse the first propagation path in order
10 to be successfully demodulated by demodulator 300c.

Half of a PN chip interval later, switch 302 toggles to provide the sample taken half a chip interval later onto line 299. The second sample is provided directly to demodulator 300b and delayed by one PN chip interval by delay element 322 prior to being provided to demodulator 300d. This
15 performs the path diversity combination as described above with respect to demodulators 300a and 300c.

The first sample is provided through switch 302 on line 298 to demodulator 300a. The sample is PN descrambled in PN descrambling element 304a. In the exemplary embodiment, PN descrambling element 204a
20 descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 206. The complex despreading operation is performed as described above with respect to complex despreading element 150a.

The complex PN descrambled sequences are provided to a first input of
25 complex conjugate multiplier 312a and to pilot filter 310a. Complex conjugate multiplier removes phase ambiguities that are introduced by the propagation path. Pilot filter 310a uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is
30 a No Op. In this special case, pilot filter 310a is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 312a which computes the dot product of the

pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 314a.

Walsh sequence multiplier 314a multiplies the input scalar sequence from complex conjugate multiplier 312a by the Walsh traffic sequence from
5 Walsh generator 318. The multiplied sequence is then provided to combiner element 224.

The first sample is redundantly provided through switch 302 on line 298 to delay element 320. Delay element 320 delays the signal by one PN chip interval prior to providing the sample to demodulator 300c. Thus, the signal
10 successfully demodulated by demodulator 300c will have traversed a propagation path that required one PN chip less time to traverse than the path that was successfully demodulated by demodulator 300a. The sample is PN descrambled in PN descrambling element 304c. In the exemplary embodiment, PN descrambling element 304c descrambles the sample in
15 accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 306.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 312c and to pilot filter 310c. Pilot filter 310c uncovers the pilot channel in accordance with the Walsh covering for the
20 pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 310c is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate
25 multiplier 212c which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 214c.

Walsh sequence multiplier 314c multiplies the input scalar sequence from complex conjugate multiplier 312c by the Walsh traffic sequence from
30 Walsh generator 318. The multiplied sequence is then provided to combiner element 324.

After one half PN chip interval, switch 302 toggles so as to put the next sample, received one half PN chip interval later, on input line 299 to

demodulators 300b and 300d. Within demodulator 300b, the sample is PN descrambled in PN descrambling element 304b. In the exemplary embodiment, PN descrambling element 304b descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 306b.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 312b and to pilot filter 310b. Pilot filter 310b uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 310b is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 312b which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 314b.

Walsh sequence multiplier 314b multiplies the input scalar sequence from complex conjugate multiplier 312b by the Walsh traffic sequence from Walsh generator 318 which is delayed by one PN chip interval by delay element 316. The multiplied sequence is then provided to combiner element 324.

The second sample is redundantly provided through switch 302 on line 299 to delay element 322. Delay element 322 delays the signal by one PN chip interval prior to providing it to demodulator 300d. Demodulator 300d successfully demodulates a signals that traversed a path that took one PN chip less time to traverse than the path successfully demodulated by demodulator 300b. The second sample is PN descrambled in PN descrambling element 304d. In the exemplary embodiment, PN descrambling element 304d descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 306.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 312d and to pilot filter 310d. Pilot filter 310d uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 310d is simply a low pass filter that removes the noise from the pilot signal. The complex

conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 312d which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 314d.

5 Walsh sequence multiplier 314d multiplies the input scalar sequence from complex conjugate multiplier 312d by the Walsh traffic sequence from Walsh generator 318. The multiplied sequence is then provided to combiner element 324.

After the demodulated signals from demodulators 300b and 300d have
10 been provided to combiner element 324, combiner element 324 combines the energies and outputs the combined energy values to accumulator 326. As described earlier, the combining operation can take many forms all of which are within the scope of the present invention. Accumulator 326 performs the integration or summation of the input symbols over the Walsh symbol
15 interval.

Turning to FIG. 8, demodulators 400a, 400c and 400e demodulate the received signal delayed with respect to one another by one PN chip interval. Similarly, demodulators 400b, 400d and 400f demodulate a second set of samples delayed with respect to one another by one PN chip interval. The
20 theory behind the operation of the demodulator of FIG. 8 is identical to that of FIG. 7. Each demodulator demodulates the signal that traversed a path that required a time to traverse differing from one another by one half PN chip interval.

The first sample is provided through switch 402 onto line 398 to
25 demodulator 400a. The sample is PN descrambled in PN descrambling element 404a. In the exemplary embodiment, PN descrambling element 404a descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 406 as described previously.

The complex PN descrambled sequences are provided to a first input of
30 complex conjugate multiplier 412a and to pilot filter 410a. Complex conjugate multiplier 412a removes phase ambiguities that are introduced by the propagation path. Pilot filter 410a uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary

embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 410a is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread
5 sequences are multiplied in complex conjugate multiplier 412a which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 414a.

Walsh sequence multiplier 414a multiplies the input scalar sequence
10 from complex conjugate multiplier 412a by the Walsh traffic sequence from Walsh generator 418. The multiplied sequence is then provided to combiner element 424.

The first sample is redundantly provided through switch 402 on line 398 to delay element 420. Delay element 420 delays the signal by one PN chip
15 interval prior to providing the sample to demodulator 400c. Thus, the signal successfully demodulated by demodulator 400c will have traversed a propagation path that required one PN chip less time to traverse than the path that was successfully demodulated by demodulator 400a. The sample is PN descrambled in PN descrambling element 404c. In the exemplary
20 embodiment, PN descrambling element 404c descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 406.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 412c and to pilot filter 410c. Pilot filter 410c
25 uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 410c is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate
30 multiplier 412c which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 414c.

Walsh sequence multiplier 414c multiplies the input scalar sequence from complex conjugate multiplier 412c by Walsh traffic sequence from Walsh generator 418. The multiplied sequence is then provided to combiner element 424.

5 The first sample is also redundantly provided through delay element 422a to delay element 422b. Delay element 422b delays the signal by one additional PN chip interval prior to providing the sample to demodulator 400e. Thus, the signal successfully demodulated by demodulator 400e will have traversed a propagation path that required one PN chip less time to
10 traverse than the path that was successfully demodulated by demodulator 400c and two PN chip intervals less than the signal successfully demodulated by demodulator 400a. The sample is PN descrambled in PN descrambling element 404e. In the exemplary embodiment, PN descrambling element 404e descrambles the sample in accordance with two PN sequences (PN_I and PN_Q)
15 provided by PN generator 406.

 The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 412e and to pilot filter 410e. Pilot filter 410e uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes
20 Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 410e is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 412e which computes the dot product of the pilot channel
25 conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 414e.

 Walsh sequence multiplier 414e multiplies the input scalar sequence from complex conjugate multiplier 412e by the Walsh traffic sequence from Walsh generator 418. The multiplied sequence is then provided to combiner
30 element 424.

 After one half PN chip interval, switch 402 toggles so as to put the next sample, received one half PN chip interval later, on input line 399 to demodulators 400b, 400d and 400f.

Within demodulator 400b, the sample is PN descrambled in PN descrambling element 404b. In the exemplary embodiment, PN descrambling element 404b descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 406b. The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 412b and to pilot filter 410b. Pilot filter 410b uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 410b is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 412b which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 414b.

Walsh sequence multiplier 414b multiplies the input scalar sequence from complex conjugate multiplier 412b by Walsh traffic sequence from Walsh generator 418. The multiplied sequence is then provided to combiner 424.

The second sample is redundantly provided through switch 402 on line 399 to delay element 420a. Delay element 420a delays the signal by one PN chip interval prior to providing it to demodulator 400d. Demodulator 400d successfully demodulates a signals that traversed a path that took one PN chip less time to traverse than the path successfully demodulated by demodulator 400b. The second sample is PN descrambled in PN descrambling element 404d. In the exemplary embodiment, PN descrambling element 404d descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 406.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 412d and to pilot filter 410d. Pilot filter 410d uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 410d is simply a low pass filter that removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 412d which computes the dot

product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 414d.

Walsh sequence multiplier 414d multiplies the input scalar sequence from complex conjugate multiplier 412d by a Walsh sequence from Walsh generator 418. The multiplied sequence is then provided to combiner 424.

The second sample is redundantly provided through delay element 420a to delay element 420b. Delay element 420b delays the signal by one additional PN chip interval prior to providing the sample to demodulator 400f. Thus, the signal successfully demodulated by demodulator 400f will have traversed a propagation path that required one PN chip less time to traverse than the path that was successfully demodulated by demodulator 400d and two PN chip intervals less than the signal successfully demodulated by demodulator 400b. The sample is PN descrambled in PN descrambling element 404f. In the exemplary embodiment, PN descrambling element 404f descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 406.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 412f and to pilot filter 410f. Pilot filter 410f uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 410f is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 412f which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 414f.

Walsh sequence multiplier 414f multiplies the input scalar sequence from complex conjugate multiplier 412f by a Walsh sequence from Walsh generator 418. The multiplied sequence is then provided to summing means 424.

After the demodulated signals from demodulators 400b, 400d and 400f have been provided to summing element 424, summing element 424 sums

the energies and outputs the summed energy values to accumulator 426. Accumulator 426 performs the integration or summation of the input symbols over the Walsh symbol interval.

Turning to FIG. 9, the baseband samples are provide to the fat finger demodulator illustrated in FIG. 9 at three times the PN chip rate. The baseband samples are provided to switch 502 which switches each subsequent sample to a different line. Demodulators 500a and 500d demodulate the received signal that are delayed with respect to one another by one PN chip interval. Similarly, demodulators 500b and 500e demodulate a second set of samples delayed with respect to one another by one PN chip interval. Lastly, demodulator 500c demodulates a set of samples that is unique from those provided to demodulators 500a, 500b, 500d and 500e. The theory behind the operation of the demodulator of FIG. 9 is identical to that of FIG. 8. Each demodulator demodulates the signal that traversed a path that required a time to traverse differing from one another by one half PN chip interval.

The first sample is provided through switch 502 onto line 499 to demodulator 500a. The sample is PN descrambled in PN descrambling element 504a. In the exemplary embodiment, PN descrambling element 504a descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 506.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 512a and to pilot filter 510a. Complex conjugate multiplier 512a removes phase ambiguities that are introduced by the propagation path. Pilot filter 510a uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 510a is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 512a which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 514a.

Walsh sequence multiplier 514a multiplies the input scalar sequence from complex conjugate multiplier 512a by the Walsh traffic sequence from Walsh generator 518. The multiplied sequence is then provided to combiner 524.

5 The first sample is redundantly provided through switch 502 on line 499 to delay element 522. Delay element 522 delays the signal by one PN chip interval prior to providing the sample to demodulator 500d. Thus, the signal successfully demodulated by demodulator 500d will have traversed a propagation path that required one PN chip less time to traverse than the
10 path that was successfully demodulated by demodulator 500a. The sample is PN descrambled in PN descrambling element 504d. In the exemplary embodiment, PN descrambling element 504d descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 506.

15 The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 512d and to pilot filter 510d. Pilot filter 510c uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this
20 special case, pilot filter 510d is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 512d which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to
25 Walsh sequence multiplier 514d.

Walsh sequence multiplier 514d multiplies the input scalar sequence from complex conjugate multiplier 512d by the Walsh traffic sequence from Walsh generator 518. The multiplied sequence is then provided to combiner 524.

30 After one third PN chip interval, switch 502 toggles so as to put the next sample on input line 498 to demodulators 500b and 500e.

Within demodulator 500b, the sample is PN descrambled in PN descrambling element 504b. In the exemplary embodiment, PN descrambling

element 504b descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 506. The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 512b and to pilot filter 510b. Pilot filter 510b uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 510b is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 512b which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 514b.

Walsh sequence multiplier 514b multiplies the input scalar sequence from complex conjugate multiplier 512b by Walsh traffic sequence from Walsh generator 518. The multiplied sequence is then provided to combiner 524.

The second sample is redundantly provided through switch 502 on line 498 to delay element 520. Delay element 520 delays the signal by one PN chip interval prior to providing it to demodulator 500e. Demodulator 500e successfully demodulates a signals that traversed a path that took one PN chip less time to traverse than the path successfully demodulated by demodulator 500b. The second sample is PN descrambled in PN descrambling element 504e. In the exemplary embodiment, PN descrambling element 504e descrambles the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 506.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 512e and to pilot filter 510e. Pilot filter 510e uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, pilot filter 510e is simply a low pass filter that removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 512e which computes the dot product of the pilot channel conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 514e.

Walsh sequence multiplier 514e multiplies the input scalar sequence from complex conjugate multiplier 512e by the Walsh traffic sequence from Walsh generator 518. The multiplied sequence is then provided to combiner 524.

5 One third of a PN chip interval later, switch 502 switches so as to provide the third base band sample onto output line 497, which provides the sample directly to demodulator 500c. The sample is PN descrambled in PN descrambling element 504c. In the exemplary embodiment, PN descrambling element 504c descrambles the sample in accordance with two PN sequences
10 (PN_I and PN_Q) provided by PN generator 506.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 512c and to pilot filter 510c. Pilot filter 510c uncovers the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes
15 Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 510c is simply a low pass filter which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 512c which computes the dot product of the pilot channel
20 conjugate and the PN descrambled sequence to provide a scalar sequence to Walsh sequence multiplier 514c.

Walsh sequence multiplier 514c multiplies the input scalar sequence from complex conjugate multiplier 512c by the Walsh traffic sequence from Walsh generator 518 and provides the result to combiner 524 combines the
25 energies of the demodulated signals from demodulators 500a, 500b, 500c, 500d and 500e and provides the result to accumulator 526. As described previously there are many alternative methods of combining the demodulated data all of which are within the scope of the present invention. Accumulator 526 accumulates the combined energy values over the Walsh symbol interval
30 and outputs the result.

FIG. 10 illustrates a modification to FIG. 7 which is applicable to all of the previous embodiments illustrated in FIGS. 6, 7, 8 and 9. FIG. 10 illustrates a modification to FIG. 7 which allows for the elimination of switch 302. In

FIG. 10, four demodulators 600a, 600b, 600c and 600d are provided to demodulate paths that are a fixed half PN chip distance from one another. The received samples are provided at twice the PN chip rate to demodulators 600a, 600b, 600c and 600d. Pilot filters 610a and 610c ignore the even samples
5 and pilot filters 610b and 610d ignore the odd samples. Combiner 624 only combines demodulated odd samples from demodulators 600a and 600c with demodulated even samples from demodulators 600b and 600d.

The first sample is provided directly to demodulators 600a and 600b and is delayed by one PN chip interval by delay elements 620 and 622 before being
10 provided to demodulators 600c and 600d, respectively. The sample is PN descrambled in PN descrambling elements 604a, 604b, 604c and 604d. In the exemplary embodiment, PN descrambling elements 604a, 604b, 604c and 604d descramble the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 606. The complex descrambling operation is
15 performed as described above with respect to complex despreading element 150a.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 612a, 612b, 612c and 612d and to pilot filter 610a, 610b, 610c and 610d. Complex conjugate multiplier removes phase
20 ambiguities that are introduced by the propagation path. Pilot filters 610b and 610d ignore the first sample and all future odd samples. Pilot filters 610a and 610c uncover the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this
25 special case, pilot filter 610a and 610c are simply low pass filters which remove the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multipliers 612a and 612c which compute the dot product of the pilot channel conjugate and the PN descrambled sequence to provide scalar
30 sequences to Walsh sequence multipliers 614a and 614c.

Walsh sequence multipliers 614a and 614c multiply the input scalar sequence from complex conjugate multipliers 612a and 612c by the Walsh traffic sequence from Walsh generator 618. The multiplied sequence is then

provided to combiner element 624. Note that although PN descrambling and Walsh multiplication are provided on the first sample by demodulators 600b and 600d, combiner 624 ignores the data provided from demodulators 600b and 600d for odd samples as erroneous.

5 The second sample is, then, provided directly to demodulators 600a and 600b and is delayed by one PN chip interval by delay elements 620 and 622 before being provided to demodulators 600c and 600d, respectively. The sample is PN descrambled in PN descrambling elements 604a, 604b, 604c and 604d. In the exemplary embodiment, PN descrambling elements 604a, 604b,
10 604c and 604d descramble the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 606. The complex descrambling operation is performed as described above with respect to complex despreading element 150a.

The complex PN descrambled sequences are provided to a first input of
15 complex conjugate multiplier 612a, 612b, 612c and 612d and to pilot filter 610a, 610b, 610c and 610d. Complex conjugate multipliers remove phase ambiguities that are introduced by the propagation path. Pilot filters 610a and 610c ignore the second sample and all future even samples. Pilot filters 610b and 610d uncover the pilot channel in accordance with the Walsh covering
20 for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 610b and 610d are simply low pass filters which remove the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in
25 complex conjugate multipliers 612b and 612d which compute the dot product of the pilot channel conjugate and the PN descrambled sequence to provide scalar sequences to Walsh sequence multipliers 614b and 614d.

Walsh sequence multipliers 614b and 614d multiply the input scalar sequence from complex conjugate multiplier 612b and 612d by the Walsh
30 traffic sequence from Walsh generator 618. The multiplied sequence is then provided to combiner element 624. Note that although PN descrambling and Walsh multiplication are provided on the second sample by demodulators

600a and 600c, combiner 624 ignores the data provided from demodulators 600b and 600d for odd samples as erroneous.

After the demodulated signals from demodulators 600b and 600d have been provided to combiner element 624, combiner element 624 combines the energies and outputs the combined energy values to accumulator 626. As described earlier, the combining operation can take many forms all of which are within the scope of the present invention. Accumulator 626 performs the integration or summation of the input symbols over the Walsh symbol interval.

FIG. 11 illustrates a modification to FIG. 10 which is applicable to all of the previous embodiments illustrated in FIGS. 6, 7, 8 and 9. FIG. 11 illustrates a modification to FIG. 10 which allows for the elimination of all but one Walsh multiplier. In FIG. 10, four demodulators 650a, 650b, 650c and 650d are provided to demodulate paths that are a fixed half PN chip distance from one another. The received samples are provided at twice the PN chip rate to demodulators 650a, 650b, 650c and 650d. Pilot filters 660a and 660c ignore the even samples and pilot filters 660b and 660d ignore the odd samples. Combiner 674 only combines demodulated odd samples from demodulators 650a and 650c with demodulated even samples from demodulators 650b and 650d.

The first sample is provided directly to demodulators 650a and 650b and is delayed by one PN chip interval by delay elements 670 and 672 before being provided to demodulators 650c and 650d, respectively. The sample is PN descrambled in PN descrambling elements 654a, 654b, 654c and 654d. In the exemplary embodiment, PN descrambling elements 654a, 654b, 654c and 654d descramble the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 656.

The complex PN descrambled sequences are provided to a first input of complex conjugate multipliers 662a, 662b, 662c and 662d and to pilot filters 660a, 660b, 660c and 660d. Complex conjugate multipliers remove phase ambiguities that are introduced by the propagation path. Pilot filters 660b and 660d ignore the first sample and all future odd samples. Pilot filters 660a and 660c uncover the pilot channel in accordance with the Walsh covering for the

pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filter 660a and 660c are simply low pass filters which remove the noise from the pilot signal.

5. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multipliers 662a and 662c which compute the dot product of the pilot channel conjugate and the PN descrambled sequence to provide scalar sequences to combiner 674. Note that although PN descrambling and Walsh multiplication are provided on the first sample by demodulators 650b and 650d, combiner 674 ignores the data provided from demodulators 650b and 650d for odd samples as erroneous.

The second sample is, then, provided directly to demodulators 650a and 650b and is delayed by one PN chip interval by delay elements 620 and 622 before being provided to demodulators 650c and 650d, respectively. The sample is PN descrambled in PN descrambling elements 654a, 654b, 654c and 654d. In the exemplary embodiment, PN descrambling elements 654a, 654b, 654c and 654d descramble the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 656. The complex descrambling operation is performed as described above with respect to complex despread element 150a.

The complex PN descrambled sequences are provided to a first input of complex conjugate multipliers 662a, 662b, 662c and 662d and to pilot filters 660a, 660b, 660c and 660d. Complex conjugate multipliers remove phase ambiguities that are introduced by the propagation path. Pilot filters 660a and 660c ignore the second sample and all future even samples.

Pilot filters 660b and 660d uncover the pilot channel in accordance with the Walsh covering for the pilot channel W_{pilot} . In the exemplary embodiment, W_{pilot} is the all zeroes Walsh sequence for which the uncovering operation is a No Op. In this special case, pilot filters 660b and 660d are simply low pass filters which removes the noise from the pilot signal. The complex conjugate of the filtered pilot signal and the complex PN despread sequences are multiplied in complex conjugate multiplier 662b and

662d which compute the dot product of the pilot channel conjugate and the PN descrambled sequence to provide scalar sequences to combiner 674.

Combiner 674 combines the odd samples demodulated by demodulators 650a and 650c with the even samples demodulated by demodulators 650b and 650d. Combiner 674 can take many forms as discussed previously with respect to the previous combiners. The combined symbols are then provided to Walsh sequence multiplier 664.

Walsh sequence multiplier 664 multiplies the combined symbol sequence by the Walsh traffic sequence W_{Traffic} which is provided by Walsh sequence generator 668. The output from Walsh sequence multiplier 664 is provided to accumulator 676. Accumulator 676 accumulates the Walsh multiplied sequence to provide Walsh despread data.

FIG. 12 illustrates a modification to FIG. 7 which is equally applicable to the modification of FIGS. 6, 7, 8 and 9. FIG. 12 provides for the demodulation of four paths that are one half PN chip apart using two demodulators. Demodulator 700a demodulates two paths that are one half PN chip apart and Demodulator 700b demodulates two additional paths that are one half PN chip apart from one another and one full PN chip from the paths demodulated by demodulator 700a.

The samples are provided at twice the PN chip rate. The samples are provided directly to demodulator 700a and are delayed by one PN chip prior to being provided to demodulator 700b. The sample is PN descrambled in PN descrambling elements 704a and 704b. In the exemplary embodiment, PN descrambling elements 704a and 704b descramble the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 706. The complex descrambling operation is performed as described above with respect to complex despreading element 150a.

The complex PN descrambled sequences are provided to a first input of complex conjugate multiplier 712a and 712b and to pilot filter 710a and 710b. Complex conjugate multipliers remove phase ambiguities that are introduced by the propagation path.

In the first embodiment of pilot filters 710a and 710b, pilot filters 710a and 710b consist of two independent filters. A first of the two independent

filters processes the odd samples and a second of the two independent filters processes the even samples.

In this embodiment, a first sample is provided to pilot filter 710a and 710b, and is processed by the independent filter within it which processes the
5 odd samples. The output of the pilot filters 710a and 710b are provided to complex conjugate multipliers 712a and 712b which multiply the conjugate of the pilot filter output with the descrambled signal from PN descrambling element 704a and 704b. Note the odd descrambled symbols are complex multiplied by the odd pilot symbols.

10 In this embodiment, a second sample is provided to pilot filter 710a and 710b, and is processed by the independent filter within it which processes the even samples. The output of the pilot filters 710a and 710b are provided to complex conjugate multipliers 712a and 712b which multiply the conjugate of the pilot filter output with the descrambled signal from PN descrambling
15 element 704a and 704b. Note the even descrambled symbols are complex multiplied by the even pilot symbols.

In a second embodiment of pilot filters 710a and 710b, each pilot filter simply processes all of the samples.

The data from complex conjugate multipliers 712a and 712b are
20 provided to Walsh sequence multipliers 714a and 714b. The Walsh traffic sequence is provided by Walsh generator 718 and the product sequence is provided from Walsh sequence multipliers 714a and 714b to combiner 724. Combiner 724 combines the Walsh sequence multiplied data as described with respect to combiner 224. The combined symbols are provided to
25 accumulator 726 which accumulates the energy over the Walsh symbol length.

FIG. 13 illustrates a modification to FIG. 12. FIG. 13 essentially performs the operation as described with respect to FIG. 12 using the second implementation of the pilot filter. Demodulator 800a demodulates two paths
30 that are one half PN chip apart and demodulator 800b demodulates two additional paths that are one half PN chip apart from one another and one full PN chip from the paths demodulated by demodulator 800a.

The samples are provided at twice the PN chip rate. The samples are provided to sample combiners 834a and 834b. Sample combiners 834a and 834b receive the samples at twice the PN chip rate and sum together sample received one half PN chip apart and provide the sum to demodulators 800a and 800b at the chip rate.

The first sample is provided to sample combiners 834 and is provided through switches 832 to delay elements 828. Delay elements 828 delay the sample by one half PN chip interval before providing the sample to a first summing input of summers 830. The second sample is then provided to equalizers 834 and provided through switches 832 to a second summing input of summer 830.

The two samples are summed together by summers 830 and the output is provided by sample combiner 834a to demodulator 800a and by sample combiners 834b to delay element 822. Delay element 822 delays the result from summer 830b by one PN chip interval before providing it to demodulator 800b.

In demodulators 800a and 800b, the received summed samples are provided to PN descrambling elements 804a and 804b. In the exemplary embodiment, PN descrambling elements 804a and 804b descramble the sample in accordance with two PN sequences (PN_I and PN_Q) provided by PN generator 806. The complex descrambling operation is performed as described above with respect to complex despreading element 150a.

The complex PN descrambled sequences are provided to a first input of complex conjugate multipliers 812a and 812b and to pilot filters 810a and 810b. Complex conjugate multipliers remove phase ambiguities that are introduced by the propagation path. Complex conjugate multipliers 812a and 812b multiply the PN descramble symbols by the conjugate of the pilot filter symbols.

The data from complex conjugate multipliers 812a and 812b are provided to Walsh sequence multipliers 814a and 814b. The Walsh traffic sequence is provided by Walsh generator 818 and the product sequence is provided from Walsh sequence multipliers 814a and 814b to combiner 824. Combiner 824 combines the Walsh sequence multiplied data as described

with respect to combiner 224. The combined symbols are provided to accumulator 826 which accumulates the energy over the Walsh symbol length. Although the present invention is described with respect to traditional PN sequences such as those in IS-95, the present invention is
5 equally applicable to other spreading sequences such as Gold codes. Moreover, although coherent detection using pilot channel offer significant benefits in system performance, the present invention is equally applicable to non coherent detection methods that do not use a pilot channel.

The previous description of the preferred embodiments is provided
10 to enable any person skilled in the art to make or use the present invention. The various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without the use of the inventive faculty. Thus, the present invention is not intended to be limited to the
15 embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

WE CLAIM:

CLAIMS

1. A spread spectrum receiver for receiving multiple spread
2 spectrum signals each travelling upon a different propagation path and each
having a resultant arrival time difference with respect to one another, said
4 spread spectrum receiver comprising:

first demodulator means for demodulating a first spread spectrum
6 signal of said multiple spread spectrum signals in accordance with a first
arrival time; and

8 second demodulator means for demodulating a second spread
spectrum signal of said multiple spread spectrum signals in accordance with
10 a fixed time interval difference with respect to said first arrival time.

2. The spread spectrum receiver of Claim 1 wherein said first
2 demodulator comprises:

pseudonoise descrambling means for descrambling said first spread
4 spectrum signal in accordance with a pseudonoise sequence;

phase adjustment means for extracting a pilot signal from said
6 pseudonoise descrambled signal and multiplying said pseudonoise
descrambled signal with said pilot signal; and

8 dechannelization means for multiplying said phase adjusted signal by
an orthogonal channel sequence.

3. The spread spectrum receiver of Claim 2 wherein said spread
2 spectrum receiver further comprises pseudonoise generator for generating
said pseudonoise sequence and wherein said second demodulator means
4 comprises:

delay mean for receiving said pseudonoise sequence and for delaying
6 said pseudonoise sequence by said fixed time interval;

pseudonoise descrambling means for descrambling said first spread
8 spectrum signal in accordance with said delayed pseudonoise sequence to
provide a second pseudonoise descrambled signal;

10 phase adjustment means for extracting a pilot signal from said second
pseudonoise descrambled signal and multiplying said second pseudonoise
12 descrambled signal with said pilot signal; and

dechannelization means for multiplying said phase adjusted signal by
14 an orthogonal channel sequence.

4. The spread spectrum receiver of Claim 2 wherein said second
2 demodulator means comprises:
 delay mean for receiving said first spread spectrum signal and for
4 delaying said first spread spectrum signal by said fixed time interval to
 provide said second spread spectrum signal;
6 second pseudonoise descrambling means for descrambling said
 second spread spectrum signal in accordance with said pseudonoise
8 sequence to provide a second pseudonoise descrambled signal;
 second phase adjustment means for extracting a pilot signal from said
10 second pseudonoise descrambled signal and multiplying said second
 pseudonoise descrambled signal with said pilot signal; and
12 second dechannelization means for multiplying said second phase
 adjusted signal by a second orthogonal channel sequence.

5. The spread spectrum receiver of Claim 1 further comprising a
2 combiner means for receiving said first demodulated spread spectrum signal
 and said second demodulated spread spectrum signal and for combining
4 said first demodulated spread spectrum signal and said second demodulated
 spread spectrum signal to provide an improved estimate of said spread
6 spectrum signal.

6. The spread spectrum receiver of Claim 2 further comprising
2 Walsh sequence generator means for generating said orthogonal channel
 sequence and wherein said second dechannelization means further
4 comprises:
 delay element for receiving said orthogonal channel sequence and for
6 delaying said orthogonal channel sequence by said fixed time interval to
 provide said second orthogonal channel sequence.

7. The spread spectrum receiver of Claim 1 further comprising
2 switching means for providing said first spread spectrum signal to said first
 demodulator means and for switching after said fixed time interval to
4 provide said second spread spectrum signal to said second demodulator
 means.

8. The spread spectrum receiver of Claim 2 wherein said phase
2 adjustment means comprises:
 pilot filter for extracing said pilot signal from said first spread
4 spectrum signal; and

complex conjugate multiplier means for receiving said first spread
6 spectrum signal and said extracted pilot signal and for multiplying said first
spread spectrum with said extracted pilot signal.

9. The spread spectrum receiver of Claim 8 wherein said pilot
2 filter extracts said pilot signal in accordance with an orthogonal pilot
sequence.

10. A method for receiving multiple spread spectrum signals each
2 travelling upon a different propagation path and each having a resultant
arrival time difference with respect to one another, said method comprising
4 the steps of:

demodulating a first spread spectrum signal of said multiple spread
6 spectrum signals in accordance with a first arrival time; and

demodulating a second spread spectrum signal of said multiple
8 spread spectrum signals in accordance with a fixed time interval difference
with respect to said first arrival time.

11. The method of Claim 10 wherein said step of demodulating
2 said first spread spectrum signal comprises the steps of:

descrambling said first spread spectrum signal in accordance with a
4 pseudonoise sequence;

extracting a pilot signal from said pseudonoise descrambled signal;

6 multiplying said pseudonoise descrambled signal with said pilot
signal; and

8 multiplying said phase adjusted signal by an orthogonal channel
sequence.

12. The method of Claim 2 wherein said method further
2 comprises the steps of:

generating said pseudonoise sequence;

4 delaying said pseudonoise sequence by said fixed time interval;

descrambling said first spread spectrum signal in accordance with said
6 delayed pseudonoise sequence to provide a second pseudonoise descrambled
signal;

8 extracting a pilot signal from said second pseudonoise descrambled
signal and multiplying said second pseudonoise descrambled signal with
10 said pilot signal; and

12 multiplying said phase adjusted signal by an orthogonal channel
sequence.

13. The method of Claim 11 wherein said step of demodulating
2 said second spread spectrum signal comprises the steps of:

4 delaying said first spread spectrum signal by said fixed time interval to
provide said second spread spectrum signal;

6 descrambling said second spread spectrum signal in accordance with
said pseudonoise sequence to provide a second pseudonoise descrambled
signal;

8 extracting a pilot signal from said second pseudonoise descrambled
signal and multiplying said second pseudonoise descrambled signal with
10 said pilot signal; and

12 multiplying said second phase adjusted signal by a second orthogonal
channel sequence.

14. The method of Claim 10 further comprising the step of
2 combining said first demodulated spread spectrum signal and said second
demodulated spread spectrum signal to provide an improved estimate of
4 said spread spectrum signal.

15. The method of Claim 11 further comprising the steps of:
2 generating said orthogonal channel sequence; and
delaying said orthogonal channel sequence by said fixed time interval
4 to provide said second orthogonal channel sequence.

16. The method of Claim 10 further comprising the steps of:
2 first switching to provide said first spread spectrum signal; and
second switching after said fixed time interval to provide said second
4 spread spectrum signal.





FIG. 1



(PRIOR ART)
FIG. 2




FIG. 3




FIG. 4




FIG. 5





FIG. 6







FIG. 8






FIG. 10




FIG. 11




FIG. 12




FIG. 13

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/US 99/25144

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H04B1/707

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5 648 983 A (KOSTIC ZORAN ET AL) 15 July 1997 (1997-07-15) column 2, line 34 - line 67 column 3, line 51 - column 5, line 20 claim 1 figure 1	1,2,4, 10,11,13
A	EP 0 749 215 A (SHARP KK ;SHARP MICROELECT TECH INC (US)) 18 December 1996 (1996-12-18) page 4, line 15 - line 34 page 5, line 9 - line 49 figures 2-4	1-16

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

- "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
- "S" document member of the same patent family

Date of the actual completion of the international search

24 February 2000

Date of mailing of the international search report

07/03/2000

Name and mailing address of the ISA

European Patent Office, P.B. 6818 Patentplan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Barel, C

INTERNATIONAL SEARCH REPORT

International Application No

PCT/US 99/25144

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
P, X	<p>GB 2 331 901 A (MOTOROLA INC) 2 June 1999 (1999-06-02) page 2, line 12 -page 3, line 10 page 6, line 23 - line 32 page 7, line 13 -page 8, line 39 figures 1,2</p>	1, 10

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No.

PCT/US 99/25144

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 5648983	A	15-07-1997	CA 2173885 A	25-10-1996
			DE 19615257 A	31-10-1996
			JP 8307382 A	22-11-1996
EP 0749215	A	18-12-1996	US 5671221 A	23-09-1997
			JP 9008776 A	10-01-1997
GB 2331901	A	02-06-1999	AU 7861798 A	01-04-1999
			BR 9803430 A	03-11-1999
			CN 1216420 A	12-05-1999
			DE 19841148 A	01-04-1999
			FI 981939 A	17-03-1999
			FR 2768576 A	19-03-1999
			JP 11168448 A	22-06-1999
			SE 9803142 A	17-03-1999

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☒ FADED TEXT OR DRAWING
- ☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.